Printed Pages: 6

NCS-603/ECS-603

(Following Paper ID and Roll No. to be filled in your Answer Books)

Paper ID : 110603 Roll No. | | | | | | | | | |

B.TECH.

Theory Examination (Semester-VI) 2015-16

COMPILER DESIGN

Time : 3 Hours *Max. Marks : 100*

Note: Attempt questions from all Sections as per directions.

Section-A

Attempt all parts of this section. Answer in brief. **(2×10=20)**

Q1. (a) What is cross compiler?

(b) What do you mean by a regular expression?

(c) State the problems associated with the top down parsing.

(d) Differentiate quadruples and triples.

https://quescol.com | Free PYQs, Solutions, Syllabus, Notes etc

(e) Differentiate between compilers and interpreters.

(f) How YACC can be used to generate parser?

(g) Define DAG.

(h) Discuss the sub set construction algorithm.

(i) What is the role of left recursion?

(j) Discuss the challenges in compiler design.

Section-B

Attempt any five questions from this section.

2. **(10×5=50)**

(a) Construct an SLR (1) parsing table for the following grammar

S→A)

A→ A, P) (P, P

P → {num, num}

(b) Give the algorithm for computing precedence function. Consider the following operator precedence matrix draw precedence graph and compute the precedence function:-

https://quescol.com | Free PYQs, Solutions, Syllabus, Notes etc

	a	(	)	;	$
A			>	>	>
(	<	<	=	<	
)			>	>	>
;	<	<	>	>	
$	<	<			

(c) Define backpatching and semantic rules for Boolean expression. Derive the three address code for the following expression

P < Q or R < S and T < U

(d) Generate three address code for the following code

```
switch a+b
{
case 1: x =x+1
case 2: y = y+2
case 3: z=z+3
default :c=c-1
}
```


https://quescol.com | Free PYQs, Solutions, Syllabus, Notes etc

(e) Construct the **LALR parsing table** for following grammar:

$S \rightarrow AA$
$A \rightarrow aA$
$A \rightarrow b$

(f) Show that the following grammar

$S \rightarrow Aa \mid bAc \mid Be \mid bBa$
$A \rightarrow d$
$B \rightarrow d$
is LR (1) but not LALR (1).

(g) What are lexical phase errors, syntactic phase errors and semantic phase errors? Explain with suitable example.

(h) Describe symbol table and its entries. Also discuss various data structure used for symbol table.

Section-C

Attempt *any two questions* from this section. **(15×2=30)**

3. How DAG is different from Syntax Tree? Construct the DAG for the following basic blocks.

https://quescol.com | Free PYQs, Solutions, Syllabus, Notes etc

a:=b+c

b:=b-d

c:=c+d

e=b+c

Also explain the key applications of DAG.

4. Consider the following sequence of three address codes:

1. Prod: =0
2. I: =1
3. T1:=4*I
4. T2:=addr (A)-4
5. T3:=T2 [T1]
6. T4:=addr (B)-4
7. T5:=T4 [T1]
8. T6:=T3*T5
9. Prod: =Prod+T6

https://quescol.com | Free PYQs, Solutions, Syllabus, Notes etc

10: I=I+1

11: If I<=20 goto (3)

Perform Loop Optimization.

5. Write short notes:

(i) Global Data Flow Analysis

(ii) Loop Unrolling

(iii) Loop Jamming

quescol.com

https://quescol.com | Free PYQs, Solutions, Syllabus, Notes etc